

British Combo-Amp Tone and Beyond

The new BOSS BC-2 generates a classic “AC-inspired” British combo-amp tone in a compact pedal, but that’s just the starting point. With a single knob, you can instantly control a variety of sound-character parameters, and quickly tap into a full spectrum of tone. Achieve the perfect vintage sound or dial into higher gain or cleaner tone across a wider frequency range than the classic amp could provide on its own. The BC-2 also offers a natural and dynamic response to your picking nuances at any setting. This easy-to-use yet technically complex pedal takes you from authentic vintage tone to expanded new-generation performance and sound.



- ▶ Wide range of tones with a single knob — from classic crisp clean and punchy crunch to creamy overdrive with long sustain and beyond
- ▶ Natural and dynamic response to picking nuance at any knob position
- ▶ Provides warm combo tones and authentic combo-amp cabinet resonance

BC-2 Specifications

■ **Nominal Input Level** -20 dBu ■ **Input Impedance** 1 MΩ ■ **Nominal Output Level** -20 dBu ■ **Output Impedance** 1 kΩ ■ **Recommended Load Impedance** 10 kΩ or greater
 ■ **Power Supply** DC 9 V: Carbon-zinc battery (9 V, 6F22) / Alkaline battery (9 V, 6LR61), AC Adaptor (PSA series: sold separately) ■ **Current Draw** 45 mA (DC 9 V) * Expected battery life under continuous use: Carbon: 2.5 hours, Alkaline: 9 hours. These figures will vary depending on the actual conditions of use. ■ **Dimensions** 73 (W) x 129 (D) x 59 (H) mm; 2-7/8 (W) x 5-1/8 (D) x 2-3/8 (H) inches ■ **Weight** 0.44 kg; 1 lb (including battery) ■ **Accessories** Owner's Manual, Leaflet ("USING THE UNIT SAFELY," "IMPORTANT NOTES," and "Information"), Alkaline battery (9 V, 6LR61) ■ **Option (sold separately)** AC Adaptor (PSA series)

* 0 dBu = 0.775 Vrms

* The specifications are subject to change without notice.